

1. Connect the USB to the computer, start your dp3 , run Digiloader1.exe.



2. Choose the right port,select Digi1.bin,Click the button.If your dp3 dose not enter blue screen,check your setting and restart from step 1.



3. In upgrading,It should be like this until over.
Attention,It will be damaged if you remove it now.



4. Upgrade Over. Your dp3 should restart automatically.

